



Product Code

F04840

P.S.U. DIN-6
100-240VAC/24VDC-2A

Reference

4840

EAN

8424299048406

Description.

Description

- DIN-6 rail format for easy installation inside an electrical equipment box, or can be screwed directly onto the wall.
- Used to power the different equipment in a Fermax installation.
- Constructed in self-extinguishing VO material.
- Includes a set of covers to protect the connection terminals.
- The power supply cannot be connected directly to the bus, given the characteristics of the Bus 2 or DUOX systems, since the power feed and the data go through the same wires. This requires the connection module.
- The power supply connection module should be connected directly to the bus with the shortest cable distance possible.
- This module prevents the power supply from disrupting the operation of the rest of the signals that circulate through the system, and it will also allow for more power supplies to be connected if required by the system.

Technical Details

- It has two operating indicator LEDs:
 - LED ON on: indicates that the feeder is in operation.
 - OVERLOAD LED on: indicates maximum current exceeded (it will be necessary to reduce the load of the installation or add additional feeder(s)).
 - ON+OVERLOAD LED flashing: indicates short circuit.
- Feeding:

- BUS 2 system: 24 Vdc
- DUOX system: 18 Vdc
- Output current depends on the connected source. Sources up to 3.5 A.
- Input voltage System BUS 2: 24 Vdc.
- DUOX System input voltage: 18 Vdc.

Details.

Weight (kg)

0.3468

Packaging measurements

(height x width x depth) cm

6,5x11,3x9,6

Video Door Entry system

Technologie

DUOX

Manuals

- 970154 Fuente Alimentacion 24Vdc Ref 4840 V07_20.pdf

Declaration of conformity

- DOCF04840EN.pdf